



www.tualcom.com  
sales@tualcom.com

# ANTI-JAMMING

	TUALAJ <b>16300/</b> <sub>16300-D</sub> GNSS ANTI-JAM CRPA SYSTEM	TUALAJ <b>8600</b> GNSS ANTI-JAM CRPA SYSTEM	TUALAJ <b>8300/</b> <sub>8300-D</sub> GNSS ANTI-JAM CRPA SYSTEM	TUALAJ <b>8200</b> GNSS ANTI-JAM CRPA SYSTEM	TUALAJ <b>4500-D</b> GNSS ANTI-JAM CRPA SYSTEM	TUALAJ <b>4300</b> GNSS ANTI-JAM CRPA SYSTEM	TUALAJ <b>4200</b> <sub>MINI</sub> GNSS ANTI-JAM CRPA SYSTEM	TUALAJ <b>4100</b> <sub>MINI</sub> GNSS ANTI-JAM CRPA SYSTEM	<b>ANTY</b> GNSS ANTI-JAM CRPA SYSTEM
<b>Dimensions (cm)</b>	<b>16300:</b> 17 x 10 x 2.8 <b>Antenna:</b> 25Ø x 2.4 <b>16300-D:</b> 30Ø x 13.3	<b>8600:</b> 9 x 9.5 x 18.7 <b>Antenna:</b> 20Ø x 3.05	<b>8300:</b> 13.9 x 7 x 2.1 <b>Antenna:</b> 20Ø x 3.05 <b>8300-D:</b> 25Ø x 15.8	9 x 11 x 2.3	25Ø x 13.8	<b>4300:</b> 11 x 10 x 2 <b>Antenna:</b> 10.5 x 10.5 x 2.3	<b>4200 MINI:</b> 7.9 x 5.65 x 2.1 <b>Antenna:</b> 10.5 x 10.5 x 2.3	7.2 x 7.2 x 2.3	<b>ANTY:</b> 4.5 x 5.8 x 1.25 <b>Antenna:</b> 4.3 x 6.2 x 1.2
<b>Weight (g)</b>	760 / 4500	2300	410 / 4150	380	4500	440	165	190	80
<b>Power Consumption (w)</b>	< 25 W	< 45 W	< 24 W	< 12 W	< 30 W	< 18 W	< 12 W	< 6 W	< 3 W
<b>Antenna Array</b>	16 Array CRPA Antenna	8 Array CRPA Antenna	8 Array CRPA Antenna	8 Array CRPA Antenna	4 Array CRPA Antenna	4 Array CRPA Antenna	4 Array CRPA Antenna	4 Array CRPA Antenna	2 Array CRPA Antenna
<b>Simultaneous Independent Nulling</b>	15	7	7	7	3	3	3	3	1
<b>Nominal Wideband Suppression</b>	>50 dB	>50 dB	>50 dB	>50 dB	>50 dB	>40 dB	>40 dB	>40 dB	>40 dB
<b>Embedded GNSS Receiver (Optional)</b>	✓	✓	✓	✓	✓	✓	✓	✓	✓
<b>RTCM Support</b>	✓	✓	✓	✓	✓	✓	✓	✓	✓
<b>Environmental Tests</b>	MIL-STD-810G	MIL-STD-810G	MIL-STD-810G	MIL-STD-810G	MIL-STD-810G	MIL-STD-810G	MIL-STD-810G	MIL-STD-810G	MIL-STD-810G
<b>EMI/ EMC</b>	MIL-STD-461F	MIL-STD-461F	MIL-STD-461F	MIL-STD-461F	MIL-STD-461F	MIL-STD-461F	MIL-STD-461F	MIL-STD-461F	MIL-STD-461F
<b>Data Interfaces</b>	Serial RS-485 Serial RS-232	Serial RS-485 Serial RS-232 Ethernet (Optional)	Serial RS-485 Serial RS-232 Ethernet (Optional)	Serial RS-485 Serial RS-232 (Optional)	Serial RS-485 Serial RS-232 Ethernet (Optional)	Serial RS-485 Serial RS-232 Ethernet	Serial RS-485 Ethernet	Serial RS-485	Serial RS-485
<b>Number of Simultaneously Protected Bands</b>	3	6	3	2	5	3	2	1	1
									